

Burmester Web-User Interface

Burmester

Burmester web user interface

The **Burmester web user interface (Web-UI)**, available in English, enables easy access to all functions and settings of the Burmester network products from any PC, Mac or tablet with a web browser. The range of functions of the **Web-UI** goes well beyond that of the Burmester **Conduct app**. It is possible to configure custom settings for your Burmester network device using the **Web-UI**. Some functions of your network product, such as **importing audio files**, are only accessible via the **Web-UI**.

Please also read the **operation manual** for your Burmester device.

Table of contents

Requirement for accessing the Web-UI	4
Accessing the Web-UI	5
Homepage	6
Playback list	7
Options in the playback list	7
Where are personal playlists saved?	7
Track list	8
Main menu	9
CD rip	9
Import	10
Import sources	10
Import of HighResAudio and Qobuz	10
Import from USB or network share	10
Edit	11
Edit – Homepage	11
Categories and editing options	11
Edit – Album editing	14
Editable album information	14
More editing options	14
Edit – Playlist editing	15
Settings	16
Setting options in the Web-UI	16
Device Settings	16
Media Settings	18
Online Services	21
Backup / Restore	23
Maintenance	24

Information	26
Legal Information	27
Messages	27
Help / Service	27
Shutdown	28
Restart	28

Requirement for accessing the Web-UI

To operate your device with the **Web-UI** you will need:

- A web browser
- A network connection to your Burmester device

Information on establishing a LAN or Wi-Fi connection can be found in the **operation manual** for your device.

This is available at www.burmester.de/en/ in the product download area or on the Web-UI at Settings >> Help /Server >> Manuals.

Accessing the Web-UI

You can reach the user interface by entering the web address (URL) or the IP address in the address line of your web browser.



111 Musiccenter

URL: <http://musiccenter111.local>

IP address: On the device >> Settings >> Info >> Network



150 Networkplayer

URL: <http://networkplayer150.local>

IP address: Via your router – settings vary



151 Musiccenter MK1 & MK2

URL: <http://musiccenter151.local>

IP address: Shown in the display after entering the remote control code OSD-1-1-1



161 All-in-One

URL: <http://allinone161.local>


IP address: Shown in the display after entering the remote control code OSD-1-1-1




Note: If there is an existing network connection, the IP addresses are also displayed in the Burmester MC app under the device name.

Homepage










- On the homepage of the **Web-UI**, the available sources are displayed in the left column.
- The header shows the playback and volume controls.







Playback list



OPTIONS IN THE PLAYBACK LIST

-  Returns to the previous page
-  Activates/deactivates the repeat function (Repeat All)
-  Activates/deactivates random playback
-  Activates edit mode
-  Shows the move and delete option
-  Moves tracks/radio stations within the playback list
-  Deletes tracks/radio stations from playback list
-  Saves the current playback as a playlist
-  Searches tracks, albums, artists, radio stations

WHERE ARE PERSONAL PLAYLISTS SAVED?

- | | | | | |
|---|--------------|---|---------------|------------------|
|  | Local Player | ▼ | Playlists | |
|  | TIDAL | ▼ | My Collection | → My Playlists |
|  | QOBUZ | ▼ | My Playlists | |
|  | IDAGIO | ▼ | Collection | → Playlists |
| | ▼ | | Dropdown Menu | → Next Menu Item |


Track list






After clicking on an album or a playlist, the track list opens.
Clicking on a track adds it to the playback list.

	<div><div></div><div>Playlist / Album name</div></div>	Track number	Total length		
1	<div>Interpret</div> <div>Track title</div>		1:23		
2	<div>Interpret</div> <div>Track title</div>		2:41		
3	<div>Interpret</div> <div>Track title</div>		3:45		
4	<div>Interpret</div> <div>Track title</div>		4:02		
5	<div>Interpret</div> <div>Track title</div>		5:12		
6	<div>Interpret</div> <div>Track title</div>		3:32		
7	<div>Interpret</div> <div>Track title</div>		17:28		

- Opens the options to add all tracks to the current playback list or to clear the playback list and load the album/playlist.
- Previews track via Web-UI, during playback is displayed
- Adds track to favourites list, once added the icon will change to
- Displays the entire recording (Idagio only)

Main menu

In the **Web-UI**, the main menu is located at the bottom right of the screen. Clicking  opens the menu and provides the following options:

-  Opens the main page of the **Web-UI** with the source overview
-  Opens the start page for the Import area – see Import
-  Opens the homepage for the Edit area – see Edit
-  Opens the Settings homepage
-  Enables Web-UI help. The different areas of the **Web-UI** are marked in colour. After clicking an area, a description of the area is displayed.

CD rip

If you select the CD rip function after inserting an audio CD, the CD will be analysed. If matching entries are found in the offline or online database, these entries will be displayed. After selecting the appropriate album, you have the option to select the tracks you want and edit the following information:

- Album
- Artist
- Genre
- Year
- Composer
- Orchestra
- Conductor
- Track title

You can then start the rip process. There is a “Fast” option suitable for new or undamaged CDs, and an “Accurate” option for scratched CDs. After completion, the album is available in the local database.

Import

IMPORT SOURCES

Music files can be imported from the following sources:



- Music content purchased from Qubuz and HighResAudio
- USB storage device
- Audio files via a network share
- Audio CD




IMPORT OF HIGHRESAUDIO AND QOBUZ

Content that is purchased and available for download is stored in the local database and can be accessed via the local player.

IMPORT FROM USB OR NETWORK SHARE

Insert a USB stick with supported audio files or copy the selected files to the \\Device IP address\Transfer share.

Open the Import area from the main menu using  >> .

Select , followed by  for USB or  for network share and  to read the source.

All audio files that can be imported are stored in the “Sandbox” until they are imported. Like in the Edit area, you have the option of editing all content before importing.



For more information, see Edit – [Album editing](#)

Please note:


Scanning and importing will take some time. The progress is shown on the screen. Please do not interrupt the process. The total amount of data per import should not exceed 50 GB. Disconnect your USB storage device after the import is complete. The transfer folder empties automatically after the scan.

Edit

EDIT – HOMEPAGE

Call up the Edit homepage using  → 

Categories and editing options



Artist



Selects artist (multiple artists can be selected)



Adds all of the artist's albums to a new or existing playlist



Renames artist



Assigns all of the artist's albums to an existing or new artist



Deletes artist and associated albums
(corresponding titles in saved playlists are then no longer available)



Note: Clicking on the artist cover area takes you to the album overview with the corresponding editing options



Album



Selects album (multiple albums can be selected)



Adds album to a new or existing playlist



Renames album



Assigns album to an existing or new artist



Deletes album
(corresponding titles in saved playlists are then no longer available)



Note: Clicking on the album cover area switches to the Edit album view with the corresponding editing options.



Genre



Selects genre (multiple genres can be selected)



Adds all albums of a selected genre to a new or existing playlist



Renames genre



Assigns all albums of the selected genre to an existing genre
Create a new genre using Settings >> Media Settings >> **Genre** Settings. For more information, see Genres on page xx)



Deletes all albums of the selected genre
The genre itself is not deleted, but is no longer displayed.)



Note: Clicking on the album cover area switches to the Edit album view with the corresponding editing options.



Playlists



Selects playlist (multiple playlists can be selected)



Adds playlist to a new or existing playlist



Renames playlist



Assigns playlist to an existing playlist



Deletes playlist



Advanced options after single or multiple selection



Select all



Cancel selection



Adds selected items to a new or existing playlist



Deletes selected items



Exports selected playlists to a USB storage device
(Only available in the “Playlists” section)



Search



EDIT – ALBUM EDITING

Editable album information:






- Album
- Artist
- Genre
- Year
- Composer
- Orchestra
- Conductor

More editing options:

Cover and booklet:

-  Adds/removes album art / advanced search on the Internet
-  Adds/removes/displays booklet

Title list:

-  Title selection (multiple titles can be selected)
-  Displays the following title information and options
 - Import Type (rip / file import / Qobuz / HighResAudio)
 - Import date
 - Audio format
 - Save the audio file
 - Listen to track (must be supported by browser)
-  Adds tracks to a new or existing artist or album
-  Deletes title
-  Moves title

EDIT – PLAYLIST EDITING

Editable playlist information: Playlist name

More editing options:

Title list:



Title selection (multiple titles can be selected)



Displays the following title information and options:

- Import Type (rip / file import / Qobuz / HighResAudio)
- Import date
- Audio format
- Save the audio file
- Listen to track (must be supported by browser)



Copies tracks to an existing playlist



Removes title from playlist



Moves title





Search

Settings

SETTING OPTIONS IN THE WEB-UIS



Note: Not all Burmester network devices offer all of the setting options described.

Main menu	Submenu	Options
 Device Settings	General Settings	Custom Name Define a name for the Burmester device Note: The name is also used to identify the device on the network
		Time Zone Sets the time zone for your device
	Energy Settings	Energy Saving Turns off the device after the set period of inactivity
		Server Mode UPnP/DLNA devices can stream from the hard drives. All other areas of the device are switched off
	Network Settings	Network Configuration <ul style="list-style-type: none">Standalone, Wi-Fi active, static IP The device can only be reached via its own Wi-Fi access point. Online services are not accessible in this modeCable to LAN, Wi-Fi active, DHCP Uses the LAN interface for network connection. The IP address is assigned by your router/ DHCP server. A Wi-Fi access point is set upCable to LAN, Wi-Fi active, static IP Uses the LAN interface for network connection. Network settings are entered manually. A Wi-Fi access point is set up

- Cable to LAN, Wi-Fi off, DHCP

Uses the LAN interface for network connection. The IP address is assigned by your router/DHCP server. A Wi-Fi access point is not set up

- Cable to LAN, Wi-Fi off, static IP

Uses the LAN interface for network connection. Network settings are entered manually. A Wi-Fi access point is not set up

- Wi-Fi Client, DHCP

Uses the Wi-Fi network to connect the device as a client. The IP address is assigned by your router/DHCP server. A Wi-Fi access point is not set up

- Wi-Fi Client, static IP

Uses the Wi-Fi network to connect the device as a client. Network settings are entered manually. A Wi-Fi access point is not set up

- Wi-Fi Setup Mode

Identifies available Wi-Fi networks to which the device can connect as a client
“Accept” confirms the selection

- WAC Setup

Takes over the network communication of other IOS devices if required

Audio Settings

Audio Profile

Adapts the analogue audio outputs to the device environment

Is the 151 connected to a power amplifier?

Choice of 4 level ranges from low to high to adapt to power amplifiers





Is the 151 connected to a preamplifier?

Choice of 4 level ranges from low to high to adapt to preamplifiers

Smooth Effect

Enables/disables smooth effect for all internal sources. This ensures a full, detailed sound, even at low volume

Gain Value

Gain value for all internal sources. If necessary, adjusts the volume to other sources

SRC (Sample Rate Converter)

Required sample rate for all internal sources

Phase

Phase rotation at the XLR outputs for all internal sources by 180°

Note: Internal sources include streaming services, Internet radio, local player and USB

Start Volume

- Selected: The device starts with the last set volume
- Not selected: The device always starts with the volume preset here



Display Settings

Display Brightness

Dims or turns off the device display



Media Settings

Playback Settings

Autoplay

Automatically plays CD/USB media after insertion

Gapless Playback

Switches gapless playback on/off for supported sources

Volume Correction

Switches automatic volume adjustment on/off for supported sources

MP3 Quality

Imported or ripped files are also saved as MP3 files to allow access to all network devices. Select the quality for the MP3 files. Changing this setting only affects newly imported or ripped files.

Rebuild all MP3 files

Reproduces all saved music titles as MP3 files with the desired resolution. Depending on the size of your music library, this process can take a long time. The process runs in the background.

Download Format






Specifies the download format for the file browser

Artist Info Language

Sets the language for artist information for local music files. If you change this setting, your device will rewrite all artist information in the background. Depending on the amount of data, this process can take some time.

Genre Settings**Add / Delete Genres**

This section allows you to choose which default genres you can assign for each rip or import. In addition, you can create your own subgenres to optimise your music collection. Genres that contain albums can no longer be edited or deleted. Empty genres that are not required can be shown and hidden using the “Visible” checkbox

	UPnP / DLNA Settings	<p>Server Mode</p> <p>In Server Mode you can stream music from your Burmester device to your TV, smartphone, tablet or streaming device.</p> <p>Use your device as a Server</p> <p>Configuration of UPnP/DLNA server settings and corresponding client devices</p> <p>activate UPnP/DLNA Server on this device</p> <p>Activates Server Mode</p> <p>Show Server Status / Restart</p> <p>Shows the server status or restarts the server</p> <p>Recent client devices</p> <p>Lists all client devices available on the network</p> <p>Functions</p> <p>Here, you can set the device properties of your client. If you are not sure which formats the device supports, please refer to the client manual or ask your retailer</p> <p>Custom Name</p> <p>Changes the name of the device</p> <p>Deletes client from the list</p> <p>Client Mode</p> <p>In Client Mode, you can stream music from a UPnP/DLNA compatible server to your Burmester device</p> <p>activate UPnP/DLNA Client on this device</p> <p>Activate Client Mode</p> <p>enable remote control for external applications</p> <p>Allow remote control by external applications</p> <p>Recent Server devices</p> <p>Lists all servers available on the network</p> <p>Functions</p>
		
		
		
		
		



Only hide this device
Hides the selected server from the list
Hide all servers of this type
Hides all servers of the selected type from the list



Delete the selected server from the list
Server List Reset
Clear List
Clears the complete list and creates a new scan

Share Settings
(Sonos)

Network sharing for client devices without UPnP/DLNA support.



Enable Share Folder
Allows access to the music files stored as MP3 under:
<\\192.168.20.35\\Sonos\\>



Online Services

HighResAudio

Access to the HighResAudio Online Store
(Requires a user account to log in)

Current state/User Name
Displays the current status and user name.
If the device is successfully connected to a user account, you will see:
“HighResAudio account successfully connected to this device, all purchases will be downloaded and imported automatically”.

Disconnect
Disconnects from HighResAudio

Purchased Media
Shows the downloaded music tracks sorted by purchase date or name

TIDAL

Authenticate and connect now
Opens the Tidal website

The login links the device to the Tidal user account.

Unlink this device from my Tidal account
Disconnects from your Tidal user account

Streaming Quality
Choice between low, high and loss-free streaming quality

QOBUZ

Access to the Qobuz Online Store
(Requires a user account to log in)

Current state/User Name
Displays the current status and user name.
If the device is successfully connected to a user account, you will see:
“Qobuz account successfully connected to this device, all purchases will be downloaded and imported automatically”.

Disconnect
Disconnects from Qobuz

Streaming Quality
Choice between low, high and HighRes streaming quality

Import Purchases Automatically
Enabled: Qobuz purchases are imported automatically
Disabled: Qobuz purchases must be manually selected for import



Purchased Media
Shows the downloaded music tracks sorted by purchase date or name

IDAGIO

Access to the Idagio website
(Requires a user account to log in)

Current state/Account Subscription
Displays the current status and user name.
If the device is successfully connected to a user account, you will see:
“Idagio account successfully connected to this device”.

Streaming Quality
Choice between low, high and loss-free streaming quality

		AirPlay (161, 232)	ON/OFF Enables or disables the AirPlay function
			AirPlay Password Allocates a password that must be entered when connecting to the Burmester device via AirPlay.
			Tune In/Airable Provides countless Internet radio stations.
			Preferred Stream Format (not applicable from software version 4.50) Choice between AAC and MP3 AAC achieves better sound quality than MP3 at similar bit rates.
		Internet Radio	Suggest new Radio Station Suggest absent radio stations Enter the station name, country and the station website and confirm with “Send Suggestion”.
			Backup / Restore Backup To avoid data loss, it is advisable to regularly backup music files to an external hard drive. The internal hard drives cannot be used for this.
			Last backup of this Device Displays the last backup. Never: No backup Connect an empty external hard drive to an unused USB port on your Musiccenter. A USB3 device may require an external power supply
			Include sample files (MP3) Also saves the automatically generated MP3 files
			Include online service account data Also saves the access data for the online services

Continue

Starts the backup process

If more than one external USB drive is connected, select one for backup

If the USB drive is suitable,

“Test passed – Backup possible”

will be displayed

Backup on this device

Starts the backup – all previous

data on the drive will be erased

Performing Backup

Performs the backup

All other services are unavailable

during backup

Restore music and data from a previous backup

If you lost your data or bought a new Burmester device, you can restore your music and data from a backup.

Please note: Restoring will replace all music and data currently stored on that device.

Connect the hard drive with the backup to an unused USB port on your Musiccenter. A USB3 device may require an external power supply

Continue

Starts the restore process

To avoid inconsistencies with imports or databases, you can perform a system check of your music and data.

Note: This process can take different amounts of time depending on the size of your library and database. There may be a delay on the device while the system check is being performed.

Restore



Maintenance

System Check



The system check searches for missing links.
Incorrectly linked data cannot be played back.

The following is checked:

- Whether there is data without corresponding database entries
- Whether there are database entries without associated data
- Whether there are incorrect database entries

OK – no action required

Warning – requires an action:

Show System Check Result

Displays the result of the system check

Delete these files and folders

Deletes the erroneous data found



Software Update

Information about software updates for your Burmester device.

To update the device, an online update can be used, an external USB drive with the update file can be connected, or the software update can be uploaded manually

A successful software update is indicated in the **Messages** section in the Settings area of this device.

Regular Update

The device regularly checks online whether updates are available. The currently installed software version is displayed

Manual Update

With Choose File, you can select a software update on the computer and carry out the update manually

Local DB Update

In offline mode, the device uses an internal database to recognise and assign CD content



Information

Disk Space /
Temperature

Check for new version

Checks for updates

There is no newer version available

Indicates that the installed
software version is up to date

A new version is available. Install now

Indicates that there is a new software
version and starts the installation

Latency /
CPU Usage /
Ram Status

Displays free disk space and the
current temperature of the processor
(CPU) and data storage (RAID)

Displays current information
about latency, CPU usage and the
RAM status of the device

Latency

Shows the delay between
incoming and outgoing data

CPU Usage

Displays overall system activity
High CPU usage can occur during
processes such as backup/restore
and system check.

RAM Status

Shows the status of the RAM

Drive Status

SSD (System)

Displays information about the installed SSD

RAID (User Data)

Displays information about the installed RAID

Device / Database
Information

Displays device information and statistics

Device Information

Shows serial number, software
version, IP addresses etc.

Statistics

Shows the number of saved artists, albums, tracks, playlists and Internet radio stations

Albums origin

Shows the origin of the saved albums

Queues

MP3 Queue

Shows the MP3 conversion progress

Gain Queue

Shows the volume adjustment progress of imported files

Print Album List

Generates a printable list of saved music data
Depending on the size of the collection, this may take some time

Generate complete Album List
Creates a complete list
Generate filtered Album List
Creates a filtered list
Various filter criteria are available in the selection field
The search can be further restricted in the input field

Generate

Creates the list and opens it in a new browser window



Legal Information

Copyright
Used Licences
Privacy Policy

Legal information

Manufacturer/originator
Third-party software/libraries used
Data protection



Messages

Displays messages



Help / Service

- Manuals
- Request
- Burmester
- Service



Messages can be remote reports on software updates or responses to queries, as well as error messages and information about the device

Delete all messages

Deletes all saved messages

Help / Service

Opens a link to the operation manual

Opens the Service contact form

Please contact your retailer first.

To contact our Service Team

fill out the contact form.,

Accept the conditions that appear.

I'm the owner of this device. I have read, understood and I agree!

Verifies that you own the device, have read and agree to the terms

Send Request

Submits the service request



Shutdown

Shutdown of the device

YES turns off the device,

NO aborts the process

Ongoing processes are interrupted when shutting down



Restart

YES restarts the device,

NO aborts the process

Ongoing processes are interrupted during a restart

VERSION: BA_WWB-UI_EN_2-0_2309

BURMESTER HOME AUDIO GMBH

Wilhelm-Kabus-Straße 47

10829 Berlin

Deutschland

www.burmester.de